

Features

- › Specific charger LiFePO₄
- › Auto-start feature
- › Multiple active protection
- › Highly efficient
- › Digital multi-functional display



Function

- › Check that your local electricity supply corresponds to the charger's input voltage (between 180 and 240 V_{AC} 50Hz).
- › Please pay attention to the DC terminals:: Brown (red) -> positive terminal (+) , blue (black) -> negative terminal (-).
- › Then connect the DC output plug or lead to the battery terminals.
- › The RED LED2 confirms that the charger is charging. The GREEN LED2 confirms that the battery is fully charged.

Specifications

	ACE-SC1210LFP	ACE-SC1220LFP	ACE-SC1230LFP	ACE-SC1240LFP	ACE-SC1270LFP
Reference	11030-0010B	11030-0020B	11030-0030B	11030-0040B	11030-0070B
Input voltage	100-240 V _{AC}				
Frequency	47-63 Hz				
Output voltage	14.6 V _{DC} +/- 0.2 V				
Output current	10 A	20 A	30 A	40 A	70 A
Reverse voltage protection	Automatic				
Short circuit protection	Automatic				
High voltage protection	Current limitation				
Dimensions	60 x 50 x 150 mm	118 x 58 x 190 mm	105 x 70 x 280 mm	135 x 75 x 300 mm	175 x 110 x 400 mm
Weight	0.6 Kg	1.2 Kg	1.8 Kg	2.3 Kg	5.3 Kg